

HUNTER-PRO PANELS - COMPARISON TABLE			
	Hunter-Pro 832	Hunter-Pro 896	Hunter-Pro 8144
Panel			
Basic number of zones	9	9	9
Maximum number of zones	32	96	144
Zone doubling	Yes		
E.O.L Resistors value	(10K + 10K)	(10K + 13K)	(5.6K +6.8K)
Max. no. of wireless zones	24	32	32
Basic number of outputs	7 (fully programmable)		
Max. no. of outputs (fully programmable)	50	58	63
Individual siren outputs	Siren can be programmed to any output		
Serial Output for	Building Management, Home automation, local and remote Monitoring, net4pro, VVR		
Wired Expansions			
EXP-PRO (8 zones)	1 max.		
IO-8N (8 zones + relay)	3 max.	11 max.	16 max.
IO-16 (16 zones + relay)	1 max.	5 max.	8 max.
IO-8NP (8 zones + relay + P/S control (1A))	3 max.	11 max.	16 max.
IO-16P (16 zones + relay + P/S control (3A))	1 max.	5 max.	8 max.
Output Expansions			
OUT-1000 (8 transistor)	1 max.		
IO-R (8 relays)	4 max.	4 max.	4 max.
Wireless Expansion			
IO-WN433 (Visonic receiver)(32 zones + 24 keyfobs)	1 max.		
Users			
User codes (4 to 6 digits)	32	96	144
Key fobs	24		
RFiD proximity cards	32	96	144
Automatic Arming (option)	Active/passive per partition or day		
Fast Arming (option)	Yes		
Final door (option)	Yes		
Keypads			
Number of keypads (supervised)	8		
Number of partitions	16		
Partition status display	Displays partition name		
RXN-400 or RXN-410 or RXN-416	Yes		
RXN-400ACE for RFiD cards	Yes		
Communication Paths			
PRE-ALARM report	Yes		
PSTN communicator built-in	Yes		
TRV/U-100 long-range radio	Yes		
GSM-200 support	Yes		
GSM to private number	Yes		
SMS-100 support	Yes		
net4pro (TCP/IP) support	Yes		
Programming			
Installer access to programming	Direct		
Technician access to user menu	Yes		
Fast programming	7 programs (PRG832) / (PRG896) / (PRG8144)		
Partial upload	Yes		
Battery test	Yes		
Telephone line test	Yes		
Technician visit report	Yes		
Copy zone programming	Yes		
Other			
Memory log	512	512	1000
Non-volatile memory log	128	240	512
Selective channel report for arm/disarm	Yes		
Duplicate user code prevention	Yes		